

Comment on ‘Aharonov–Casher-Effect Suppression of Macroscopic Tunneling of Magnetic Flux’

Alec Maassen van den Brink*

D-Wave Systems Inc., 320-1985 West Broadway, Vancouver, BC, V6J 4Y3, Canada

(Dated: February 1, 2008)

A recent Letter [1] has proposed a device, consisting of an rf SQUID with the junction replaced by a double one, i.e. a Bloch transistor. For symmetric Josephson couplings $E_1 = E_2$, and for specific flux bias Φ_x and gate voltage V_g applied to the transistor’s island, the tunneling of encircled flux Φ between its two local potential minima is claimed to be suppressed completely due to destructive interference. This comment purports to show that this claim in general is not valid. Namely, the very Hamiltonian (1) in [1], from which the effect is derived, describes the circuit only under an additional condition.




FIG. 1: A superconducting ring including a Bloch transistor.

For definiteness, we model the circuit as in Fig. 1. The stray capacitance C_s is formally necessary if V_g is to have any effect; otherwise, the charge on the gate capacitor C_g is conserved [2]. Thus, the effective environment is $C_e^{-1} = C_s^{-1} + C_g^{-1}$. A symmetric setup with a second inductance L' between C_s and C_2 would create a third degree of freedom: a resonance with $\omega_{\text{res}}^2 = C_e^{-1}[L^{-1} + (L')^{-1}]$, coupling to the Josephson phases $\phi_{1,2}$. Similarly if instead a C'_s would be inserted between L and C_1 or parallel to L or if, most physically, C_s were taken distributed along the ring. In all these alternatives, the additional high-frequency modes can be ignored at low energy and our conclusion would hold unchanged.

For the Hamiltonian one obtains ($\hbar = 1$)

$$H = Q_1^2/2C_1 + (Q_2 - C_e V_g)^2/2(C_2 + C_e) - E_1 \cos \phi_1 - E_2 \cos \phi_2 + (\phi_1 + \phi_2 - 2\pi\Phi_x/\Phi_0)^2/8e^2 L; \quad (1)$$

Φ_0 is the flux quantum. Q_2 , the conjugate to ϕ_2 , has a contribution on C_s besides the charge across C_2 . Our basic environment thus merely renormalizes C_2 [3]. Now put $\phi \equiv \phi_1 + \phi_2$, $2\theta \equiv \phi_1 - \phi_2$, implying $2Q_\phi = Q_1 + Q_2$, $Q_\theta = Q_1 - Q_2$. The $Q_{\phi,\theta}$ capacitance matrix is $\mathbb{C} = \begin{pmatrix} \frac{1}{2}(\tilde{C}_1 + \tilde{C}_2) & \frac{1}{2}(\tilde{C}_1 - \tilde{C}_2) \\ \frac{1}{2}(\tilde{C}_1 - \tilde{C}_2) & \tilde{C}_1 + \tilde{C}_2 \end{pmatrix}$, with $\tilde{C}_1 = C_1$ and $\tilde{C}_2 = C_2 + C_e$. At least in this model, the diagonal entries of $\mathbb{C}$ are still related. More importantly, $\mathbb{C}$ is not diagonal as the effective $\tilde{C}_1$ and $\tilde{C}_2$ differ in general—due to not only the environment, but mainly the inevitable fabrication spread. The cross-capacitance $C_{\phi\theta}$ adds a term $\propto C_{\phi\theta}\dot{\phi}\dot{\theta}$ to the Lagrangian (4) in [1], so that the two tunneling paths in their Fig. 2 become inequivalent and no longer cancel. For an arbitrary ratio of Coulomb and Josephson energies, the symmetries proving level degeneracy [1] require $E_1 = E_2$ and $\tilde{C}_1 = \tilde{C}_2$. It would be interesting to see if and to what extent a $C_{\phi\theta} \neq 0$ could be compensated for by a change in working point.

It may be useful to compare with the two-junction design in [4], and clarify why $C_{\phi\theta}$ does not matter there but does in [1]. In [4], ϕ is made near-classical by a large junction and capacitor, so its conjugate charge and hence the latter’s coupling to Q_θ can be ignored. Here, quantum effects in *both* phases are essential for Aharonov–Casher type interference. Indeed, the device of [1] is a modified rf SQUID, and suppressing overall-phase fluctuations in the latter would merely yield trivial classical dynamics.

In closing, let us point out that also note 22 in [1] is incorrect. A superconducting loop with only two junctions is not bistable for all L , since for $L \rightarrow 0$ the Josephson coupling is a simple cosine [5]. This is precisely the reason why the design in [6], which does not rely on magnetic energy to achieve bistability, involves *three* junctions.

I thank M.H.S. Amin, A. Blais, A. Shnirman, and A.M. Zagoskin for helpful comments.

* Electronic address: alec@dwavesys.com

- [1] J.R. Friedman and D.V. Averin, Phys. Rev. Lett. **88**, 050403 (2002).
- [2] However, while one must have $C_s \neq 0$, grounding the loop, i.e. $C_s \rightarrow \infty$, is admissible.
- [3] Clearly, in more general circuit models such as mentioned below Fig. 1 also C_1 gets renormalized. However, complete suppression of tunneling always requires fine-tuning two effective capacitances to be exactly equal.

- [4] A. Cottet *et al.*, Physica C **367**, 197 (2002); D. Vion *et al.*, Science **296**, 886 (2002).
- [5] This cosine’s amplitude vanishes iff $E_1 = E_2$ and $\Phi_x = \Phi_0/2$, in which case higher-order terms determine the potential landscape and the minima in Fig. 2 of [1] persist for small L . However, the barrier separating these minima vanishes for $L \rightarrow 0$, so that they are not “metastable flux states” in any operational sense.
- [6] J.E. Mooij *et al.*, Science **285**, 1036 (1999).